

Model:DS-2CD862F-E

Name:1.3 Mega Pixels Network Camera

Parameters

| | |
|--------------------------------|--|
| Parameter Model | DS-2CD862F-E |
| Camera | |
| Image Sensor | 1/3 inch SONY progressive scan CCD |
| Effective Pixels | 1280(H) ×960(V), 1.3M CCD |
| Min. Illumination | 0.1Lux @ F1.2 |
| Electronic Shutter | 1/4s-1/10,000 s |
| Auto Iris Lens | DC/Video |
| Lens | Option |
| Lens Mount | C/CS mount |
| Day&Night | Electronic (ICR option) |
| S/N Ratio | More than 50dB |
| Video Output | 1Vp-p Composite Output(75Ω/BNC) |
| Compression Standard | |
| Video Compression | MPEG-4 |
| Video Output | 32 K~2M, adjustable(8Mbps maximum) |
| Audio Compression | OggVorbis |
| Image | |
| Image Resolution | 1280*960, 1280*720, 640*480, 320*240 |
| Frame Rate | PAL :12.5fps(1280*960), 25fps(1280x720) NTSC:15fps(1280*960), 30fps(1280x720) |
| Functions | |
| Electronic PTZ | Support |
| Motion Detect | Support |
| Dual Stream | Support |
| SD Card Local Recording | Support |
| Heartbeat | Support |
| Password Protect | Support |
| Protocols | TCP/IP,UDP/ IP,HTTP,FTP,SMTP,DHCP,DNS,DDNS,NTP,SNMP,RTP,RTCP,PPPoE. |
| Interface | |
| Voice Talk Input | 1 channel 3.5mm audio interface(2.0~2.4Vp-p,1kΩ) |
| Voice Output | 1 channel 3.5mm audio interface(Line level, 600Ω) |
| Communication | 1 RJ45 10M/100M self-adaptive Ethernet port and 1 RS-485 interface |
| Alarm Input | 1 channel signal input |
| Alarm Output | 1 channel signal on-off output |
| Others | |
| Working Temperature | -10℃-60℃ |
| Power Supply | AC24V±10%/DC12V±10%, PoE (Power over Ethernet). |

| | |
|--------------------------|-----------|
| Power Consumption | 4W MAX |
| Dimensions (mm) | 69×59×114 |
| Weight | 600g |